

**FA-2242**

(Fault Auto Switcher)



ZOOM

PRINT

**Features**

- Two groups of 4 amplifiers + 1 stand-by amplifier.
- High Quality balanced inputs.
- Checks speaker lines and amplifiers outputs continuously.
- Individual volume adjustment of each amplifier.
- Ground fault indication by LED & buzzer.
- One group of 8 amplifiers + 1 stand-by amplifier.
- AC operation - DC 24V operation.

**Technical specifications**

<b>Signal input / output</b>	1(Level Variable)
<b>Dynamic range</b>	+18dB
<b>Frequency Response</b>	less than -0.5dB (20Hz ~ 20KHz)
<b>T.H.D</b>	less than 0.04%
<b>Signal to noise ratio</b>	less than 86dB
<b>Power consumption</b>	21W
<b>Power (option)</b>	120V/230V/240VAC 50/60Hz , 24VDC
<b>Dimensions (mm)</b>	483(W)×88(H)×200(D)
<b>Weight(kg)</b>	4.2kg

LIST