



PA – 50



| | |
|----------------------------------|--|
| TYPE | MIXER AMPLIFIER |
| MODEL | PA-50 |
| POWER SUPPLY | AC 230V 50Hz , DC 12V |
| POWER OUTPUT | 50W RMS |
| TOTAL HARMONIC DISTORTION | ≥ 1% @1 KHz |
| SENSITIVITY | 1/4" PHONE JACK (UNBALANCED) MIC 1,2,3 1.5 mV @ 600Ω RCA JACK (UNBALANCED) AUX 1,2,3 200 mV @10KΩ |
| OUTPUT | 100 V , 70 V , 8Ω , 4Ω |
| SIGNAL TO NOISE RATIO | 73 dB (full volume) 70 dB (Aux 1,2) 65 dB (Mic 1,2) |
| FREQUENCY RESPONSE | 50 Hz 15K Hz 3dB ± 3dB TREBLE 10 KHz ± 10dB BASS 100 Hz ± 10dB |
| AC POWER CONSUMPTION | 80 w @ RATED POWER |
| DC POWER CONSUMPTION | 4A @ RATED POWER |
| DIMENSION | 68mm275mmXmm225X(HWD) |
| WEIGHT | 3 KGS |
| MOUNTING | FREE STANDING |