

TA-1240

(Mixing Amplifier)

ZOOM

PRINT



Features

- Four output speaker selectors
Four separate output can be switched on /off independent using the front panel controls.
- Override Assignment for channels 1 and 2.
- Universal input
Each input is combo connector to use both XLR and 1/4" phone connectors.
- Bass&Treble Equalizer.
- External DC input.
- Chime remote
- +48 phantom power
- Bass&Treble control for pack series

Technical specifications

Input Sensitivity / Impedance	Mic / Line 1~5 : -50dBm(2.45mV) -10dBm(245mV) Tel Paging : -10dBm(245mV) Pack Unit T : -16dBm(245mV) Pre Out T : +4dBm (1.23V) AMP in : +4dBm (1.23V)
Rated Output	240w (RMS)
Output Impedance	Low IMP : 8Ω, 2.6Ω
	Europe : 100V
	America : 70V
Frequency Response(Line signal)	Less Than -3dB(80Hz ~ 15kHz)
Signal to Noise Ratio	Line : More than 70dB
	Mic : More than 60dB
T.H.D	Less Than 6% (1kHz)
Power consumption	625W
1/8 Power Current draw 120V/230V	2.55A / 1.35A
Rated Power Current draw 120V/230V	6.2A / 3.48A

Power Source(Option)	120V/220V/230V/240VAC 50~60Hz, 24VDC
Dimensions (mm/ inch)	483(W) X 133(H) X 350(D) 19(W) X 5.2(H) X 13.8(D)
Weight(kg/lbs)	13.5kg

[LIST](#)