

**DR-1104**

(Data RX)



ZOOM

PRINT

**Features**

- Superior audio circuit for the long distance with balanced circuit(separate cable).
- priority (E/M) will mute all RA-1051A/B.
- Up to 4pcs of 20-zone paging microphone's RA-1051A/B.
- 4 LED indicators "BUSY"to monitor the status.
- RS485 data communication to RA-1051A/B (UTPcat 5).

**Technical specifications**

<b>Input Sensitivity / Impedance</b>	Nor +4dBu/600 Ω bal.
<b>Output Impedance</b>	Nor +4dBu/600 Ω bal.
<b>Frequency Response(Line signal)</b>	Less than -1dB (20Hz-20kHz).
<b>Signal to Noise Ratio</b>	More than 86dB
<b>T.H.D</b>	Less than 0.02%
<b>Power consumption</b>	3.6W
<b>Power</b>	DC 24V
<b>Dimensions (mm)</b>	483(W) x 44(H) x 200(D)
<b>Weight(kg)</b>	2.7kg

LIST