

## TA-1060/1120

(Mixing Amplifier)

ZOOM

PRINT



### Features

- Pre-amp out/ amp-in for extensions to power amplifiers.
- Individual gain control for channel 1~5.
- 4 Mic input + 4 line inputs two/four tone Chime, 2 siren tones.
- Voice priority for Mic 1.
- Telephone Input & Music On hold ( tuner only).
- Optional modules.  
(Tp-100, DM-100, CDP-100, CDR-100)
- Bass/ treble tone control.
- 4 speaker outputs.
- Remote Chime with external terminal.
- Individual 4 Zone speaker selector.
- VU output meter.
- 100V/ 70V output selector.
- AC/ DC 24V
- Bass & Treble control for Pack Series.
- Phantom power on Mic 2,3

### Technical specifications

<b>Rated power ( at 1% THD)</b>	TA-1120 : 130W
	TA-1060 : 70W
<b>Frequency response (±3dB)</b>	80Hz to 15kHz
<b>THD at 1kHz (rated output)</b>	Less than 1%
<b>Equalizer</b>	Bass : ± 10dB at 100Hz
	Treble : ±10dB at 10kHz
<b>Signal to Noise Ratio</b>	Line : better than 70dB
	Mic : better than 60dB
<b>Input</b>	Mic 1~4 : 3mV
	Line : 300mV
	Phone : 2.4mV
<b>Power source</b>	120,230,240V AC, 24V DC 50/60Hz
<b>Dimensions (mm/ inch)</b>	420(W) x 110(H) x 320(D)
	16.5(W) x 4.34(H) x 12.6(D)

<b>Weight(kg/lbs)</b>	TA-1120 : 12.5kg , TA-1060 : 10.5kg
-----------------------	-------------------------------------

[LIST](#)