

**BC-180 / BC-250 / BC-350**



**Features**

- 5 MIC inputs, 3 AUX and 2 LINE inputs, 1 Preamp output, 1 group of Send and Return.
- MIC 1 Priority with mute-function.
- With music tips.
- With fault indication.
- 10-segments signal level indication; treble and bass adjusters on output channel.
- Over current, overheating and short circuit protection.
- Turn on delay and DC offset protection.
- Use CMOS power transistor.
- Built-in mp3 player.
- 50-16,000Hz Frequency response, -3db, 0.1% THD.
- BC series with 6 zoning output and volume controllers.
- Output: 100V, 70V, 4~16 ohms 180/250/350WRMS (PAP180/250/350)
- Power supply: AC115V/230V, DC24V .

**Technical Specifications**

Model		BC-180	BC-250	BC-350
RATING POWER		180W RMS	250W RMS	350W RMS
Mic input	5 mV ,600 Ohms			
Line input	300 mV , 10k Ohms			
AC FUSE	5A/250V	7A/250V	10A/250V	10A/250V
DC FUSE	20A/250V	20A/250A	25A/250V	25A/250V