

## MU-2307

(Monitor Panel)



ZOOM

PRINT

### ■ Features

- Monitoring by internal speaker or headphones.
- Monitoring up to 10 channels with individual LED meters.
- Variable input signal ranges from 1v to 100v.
- Monitor level adjustment per input.
- Input level monitor adjustment

### ■ Technical specifications

<b>Input sensitivity / impedance</b>	1V-100V / 10kΩ bal.
<b>Rated monitor</b>	speaker : 2W max.
	headphone : 0.1W max.
<b>Frequency response</b>	less than -3dB(100Hz ~ 20kHz)
<b>Power consumption</b>	13W(all operation)
	9W(1ch operation)
<b>T.H.D</b>	less than 0.04%
<b>Power (Option)</b>	120V/230V/240V AC 50/60Hz , 24V DC
<b>Dimensions (mm)</b> <b>(inch)</b>	483(W) X 88 (H) X 200(D)
	19(W) X 3.5(H) X 7.9(D)
<b>Weight(kg/lbs)</b>	4.8kg

LIST