

## TU-110B

(AM/FM Tuner)


[ZOOM](#)
[PRINT](#)

### ■ Features

- Auto Store Memory Function(A/PS).
- Balanced Mono XLR Output
- Unbalanced Stereo RCA Output.
- Retains Presets When Power is Off.
- 6+6+6 FM Presets.
- 6+6 AM Presets.
- SCAN And SEEK Functions.
- Signal Strength Meter.
- Preset Memory SCAN Function(A/PS).
- Large LCD Digital Display
- AC and DC 24V operation..

### ■ Technical specifications

<b>Tuning range</b>	FM 87.5~108MHz, AM 522~1620kHz
<b>ANT input</b>	FM : 75Ω coaxial cable
	AM : Loop antenna and lead antenna
<b>Usable sensitivity</b>	FM : 2μV AM : 4.5μV
<b>Signal to noise ratio</b>	FM : 60dB AM : 45dB
<b>Memory Back-up</b>	For 45days (after AC Power Off)
<b>Variable output</b>	0.245V (-10dBm) Unbalanced
<b>Fixed output</b>	0.775V (0dBm) Balanced
<b>Power consumption</b>	7.4W
<b>Power source</b>	120V/220V/230V/240V AC 50/60Hz, 24V DC
<b>Dimensions (mm/ inch)</b>	483(W)×44(H)×120(D), 19(W)×1.7(H)×5(D)
<b>Weight(kg)</b>	3.5kg

[LIST](#)